



EASY

Ref. 07200032

PMR446 TRANSCEIVER

- High capacity Li-Ion battery pack.
- 50 CTCSS and 83 DCS codes adjustable by user with keys.
- Save energy function.
- Key-pad lock adjustable.
- SQL function adjustable by user.
- Key press beep on/off function.
- Channel scan adjustable by user.
- Battery power display.
- FM radio function (88 ~ 108 MHz).
- VOX function adjustable with optional PX-22 microphone and PX-20 microphone/earphone.

Supplied with: 7.4V/2300mAh rechargeable Li-Ion battery pack, desk battery charger, 6 AAA battery case, antenna, belt clip, italian and english user's manual.

Optional Accessories

	7,4V/2300 mAH Batteria	Ref. 07205070
	Desktop battery charger	Ref. 07205072
	Power cable with car cigarette lighter plug	Ref. 057205127
	Case for 6 AAA batteries	Ref. 07205073
MEP-409KL	Air Microphone/Earphone	Ref. 07205011
KEP-200EK	Earphone	Ref. 07205015
PX-20	Microphone/Earphone	Ref. 07205010
PX-22	Microphone/Speaker	Ref. 07205012
X-17K PLUS	Laringophone/Earphone	Ref. 07205077
	430/450MHz High gain antenna	Ref. 07205069
PX-24	USB Programming cable	Ref. 07205016
KPT-05	Belt softcase	Ref. 07205006

Technical specification

Frequency range	446.00625 ~ 446.09375 MHz
Channel	8 + 8 channels
Modulation	FM
Operating temperature range	-20°C ~ +60°C
Voltage	7,4V
Power supply	7,2V-2300mAh Li-Ion battery pack
Standby current	about 15mA
Size	100 × 58 × 36 mm
Transmitter	
Frequency stabilization	±5ppm
Output power	500 mW
Emission current	600 mA
Maximum frequency deviation	±2.5
Audio distortion	<10%
Receiver	
Sensitivity	<-122dBm (12dB SINAD)
Audio output	≥500mW
Receiving current	≤140 mA